

# LBB 4432/00 Call Station Keypad

www.boschsecurity.com



**BOSCH**  
Invented for life



- ▶ Eight freely programmable selection keys
- ▶ Serial data and power interface to call station basic
- ▶ Up to 16 keypads can be connected to one call station basic
- ▶ Activation indicator for each key
- ▶ Stylish and modern design

The call station keypad is used in combination with the call station basic to make manual or pre-recorded announcements to any assigned zones, to select the zones or to execute pre-defined actions. The call station keypad has eight programmable buttons, each with a two-color status LED.

## Functions

The keys of the call station keypad can be programmed for actions, such as:

- Controlling functions: selection recall, call activation, cancel selection, BGM off, BGM volume control, fault acknowledgement, etc.
- Selecting sources: BGM channel, pre-recorded messages, attention and alarm tones
- Selecting destinations: zones and zone groups

The keys can be programmed for different modes of operation, such as momentary or toggle. Each key has one two-color status LED beside it. Beside each LED is a transparent, removable tab that can hold a function or zone label for the key. Safety covers to prevent accidental activation of the keys are available as an option.

The keypad gets its power from the call station it is connected to.

### Controls and indicators

- Eight function keys
- Eight two-color LEDs

### Interconnections

- Two serial data and power connections

## Certifications and approvals

Safety	acc. to IEC 60065 / EN 60065
Immunity	acc. to EN 55103-2 / EN 50130-4 / EN 50121-4
Emissions	acc. to EN 55103-1 / FCC-47 part 15B
Emergency	acc. to EN 60849 / EN 54-16 / ISO 7240-16
Maritime	acc. to IEC 60945

Region	Certification	
Europe	CPR	EU_CPR
	CE	

Region	Certification	
	CE	COC
	CE	CertAlarm
	CE	DOP
	GL	
Poland	CNBOP	

### Parts included

Quantity	Component
1	LBB 4432/00 Call Station Keypad
1	Flat cable
1	Coupling bracket
1	Set of text labels

### Technical specifications

#### Electrical

Power consumption	1.5 W (DC)
-------------------	------------

#### Mechanical

Dimensions (H x W x D)	70 x 95 x 200 mm (2.8 x 3.7 x 7.9 in)
Weight	0.3 kg (0.7 lb)
Mounting	Bracket attachment to a call station or other keypad
Color	Charcoal

#### Environmental

Operating temperature	-5 °C to +45 °C (+23 °F to +113 °F)
Storage temperature	-20 °C to +70 °C (-4 °F to +158 °F)
Humidity	15% to 90%
Air pressure	600 to 1100 hPa

### Ordering information

#### LBB 4432/00 Call Station Keypad

Call station keypad with 8 programmable buttons and status indicators, up to 16 keypads can be connected to a call station.

Order number **LBB4432/00**

#### Accessories

#### LBB 4436/00 Set of Key Covers (10 pcs)

Key covers to prevent accidental key presses on LBB4432/00 keypad buttons (set of 10 pieces).

Order number **LBB4436/00**

**Represented by:**

**Americas:**

Bosch Security Systems, Inc.  
12000 Portland Avenue South  
Burnsville MN 55337, USA  
Phone: +1-800-392-3497  
Fax: +1-800-955-6831  
audiosupport@us.bosch.com  
www.boschsecurity.com

**Europe, Middle East, Africa:**

Bosch Security Systems B.V.  
P.O. Box 80002  
5617 BA Eindhoven, The Netherlands  
Phone: + 31 40 2577 284  
Fax: +31 40 2577 330  
emea.securitysystems@bosch.com  
www.boschsecurity.com

**Asia-Pacific:**

Robert Bosch (SEA) Pte Ltd, Security  
Systems  
11 Bishan Street 21  
Singapore 573943  
Phone: +65 6571 2808  
Fax: +65 6571 2699  
apr.securitysystems@bosch.com  
www.boschsecurity.asia

**China:**

Bosch (Shanghai) Security Systems Ltd.  
201 Building, No. 333 Fuquan Road  
North IBP  
Changning District, Shanghai  
200335 China  
Phone +86 21 22181111  
Fax: +86 21 22182398  
www.boschsecurity.com.cn

**America Latina:**

Robert Bosch Ltda Security Systems Division  
Via Anhanguera, Km 98  
CEP 13065-900  
Campinas, Sao Paulo, Brazil  
Phone: +55 19 2103 2860  
Fax: +55 19 2103 2862  
latam.boschsecurity@bosch.com  
www.boschsecurity.com