



PLE-WP3S2Z-EU Wall Panel



- ▶ Can be used for all Plena Easyline (PLE) mixer-amplifiers
- ▶ Remote selection of three music source inputs
- ▶ Remote zone selection
- ▶ Perfect companion to Bosch volume controls
- ▶ Daisy-chain of multiple wall panels
- ▶ Powered through the Plena system

The Plena PLE-WP3S2Z-EU Wall Panel is used to remotely select a music source and activate or deactivate zones of a Plena PLE audio mixer or mixer amplifier.

Functions

Remote zone and Input source control

Two zones and three music input sources can be controlled from a remote location by selecting the individual switches.

Indicators

The ON status of each zone and selected music source is indicated by an LED.

Connections and settings

With the use of CAT-5 cable and RJ-45 connector the PLE-WP3S2Z-EU Wall Panel can be easily and quickly connected to the PLE series mixer or mixer amplifier. Settings are not required.

Daisy chain / Remote locations

Maximum four PLE-WP3S2Z-EU Wall Panels can be daisy chained to remotely control a PLE series mixer or mixer amplifier.

Certifications and Approvals

Region	Certification
Europe	CE
Safety	acc. to EN 60065
EMC emission	acc. to EN 55103-1
EMC immunity	acc. to EN 55103-2

Installation/Configuration Notes

The Wall Panel is installed to the mixer or mixer-amplifier via standard CAT-5 cable with RJ-45 connector. The maximum cable distance is 200 m. The design and color are unobtrusive in any interior. Ease of installation, operation and reliability is optimized in the design. The appearance is matched to the Bosch Loudspeaker Volume Controls.

The wall panel buttons have the same function as the corresponding buttons of the Plena mixer front panel

Parts Included

1	PLE-WP3S2Z-EU Wall Panel
1	Quick Reference Card

Technical Specifications

Electrical

Power supply

Voltage range	5 VDC, supplied by the connected amplifier
Current consumption (typical)	<50 mA

Connectors

to (mixer) amplifier	1 x RJ-45
Loop through	1 x RJ-45

Mechanical

Dimensions (H x W x D)	87 x 87 x 21 mm (3.43 x 3.43 x 0.83 in)
------------------------	--

Weight	Approx. 0.35 kg (0.77 lb)
--------	---------------------------

Color	White
-------	-------

Label text color	Silver
------------------	--------

Environmental

Operating temperature	-10 °C to +45 °C (14 °F to +113 °F)
-----------------------	-------------------------------------

Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
---------------------	--------------------------------------

Relative humidity	<95%
-------------------	------

Ordering Information

PLE-WP3S2Z-EU Wall Panel

remotely select a music source and activate or deactivate zones of a Plena PLE audio mixer or mixer amplifier

PLE-WP3S2Z-EU

Americas:
Bosch Communications Systems
12000 Portland Avenue South
Burnsville, Minnesota 55337, USA
Phone: +1-800-392-3497
Fax: +1-800-955-6831
audiosupport@us.bosch.com
www.boschsecurity.com

Europe, Middle East, Africa:
Bosch Security Systems B.V.
P.O. Box 80002
5600 JB Eindhoven, The Netherlands
Phone: +31 40 2577 284
Fax: +31 40 2577 330
emea.securitysystems@bosch.com
www.boschsecurity.com

Asia-Pacific:
Robert Bosch (SEA) Pte Ltd
11 Bishan Street 21
Singapore 573943
Phone: +65 6571 2600
Fax: +65 6571 2698
apr.securitysystems@bosch.com
www.boschsecurity.com

Represented by