# **LB1-UW06x-x Cabinet Loudspeakers**

www.boschsecurity.com





- Good speech intelligibility and background music reproduction
- ► Available in black or white
- ▶ MDF construction
- ▶ With or without integral volume control
- Complies with international installation and safety regulations

The LB1-UW06x-x is a 6 W, general-purpose, costeffective loudspeaker for indoor use, with or without volume control. Keyholes at the rear are provided for quick and easy wall mounting. The angled front baffle results in a better sound in the listening area. The cabinet is available in black or white.

**Functions** 

The robust, solid MDF (medium density fiber board) enclosures are covered with a durable, easy-to-clean vinyl in a choice of white or black. The ABS fronts are covered with fine woven cloth in matching color. The angled front baffle results in improved high frequency reproduction in the listening area.

The speaker is available with or without a volume control.

### **Certifications and approvals**

All Bosch loudspeakers are designed to withstand operating at their rated power for 100 hours in accordance with IEC 268-5 Power Handling Capacity (PHC) standards. Bosch has also developed the Simulated Acoustical Feedback Exposure (SAFE) test to demonstrate that they can withstand two times their rated power for short durations. This ensures extra reliability under extreme conditions, leading to


higher customer satisfaction, longer operating life, and much less chance of failure or performance deterioration.

Safety acc. to EN 60065

### Installation/configuration notes

Three keyholes in the rear panel provide easy and quick wall mounting.

A convenient, easy-to-use, four-pole push-in terminal block is on the rear panel for on-site wiring. This terminal block has provision for power tapping on the 100 V, matching transformer in the cabinet. It allows selection of nominal full-power, half-power or quarter-power radiation (in 3 dB steps).




Dimensions LB1-UW06-x in mm showing volume control (1)




Circuit diagram LB1-UW06-x




Circuit diagram LB1-UW06V-x



Frequency response



Polar diagram horizontal (measured with pink noise)



Polar diagram vertical (measured with pink noise)

### **Technical specifications**

### Electrical\*

Maximum power	9 W
Rated power	6/3/1.5W
Sound pressure level at 6 W / 1 W (1 kHz, 1 m)	99 dB / 91 dB (SPL)
Sound pressure level at 6 W / 1 W (4 kHz, 1 m)	100 dB / 92 dB (SPL)
Effective frequency range	180 Hz to 20 kHz (-10 dB)
Opening angle	1 kHz / 4 kHz (-6 dB)
horizontal	165°/95°
vertical	158°/73°
Rated input voltage	100 V
Rated impedance	1667 ohm
Connector	4-pole push-in terminal block
* Table : all a afama a all table : tal IFO 00000 F	

<sup>\*</sup> Technical performance data acc. to IEC 60268-5

### Mechanical

Dimensions (H x W x D)	240x151x141/119 mm (9.4 x 5.9 x 5.6/4.7 in)
Weight	0.9 kg (2 lb)
Color	Black (D) or white (L)
cabinet / cloth (D)	Matches RAL 9004 / RAL 9004
cabinet / cloth (L)	Matches RAL 9010 / RAL 7044

### **Environmental**

Operating temperature	-25 °C to +55°C (-13 °F to +131 °F)
Storage temperature	-40 °C to +70 °C (-40 °F to +158 °F)
Relative humidity	<95%

### **Ordering information**

### LB1-UW06-D Cabinet Loudspeaker

Cabinet loudspeaker 6 W, MDF enclosure with finewoven cloth front, finished in black, with 3 keyholes for wall mounting.

Order number LB1-UW06-D

## LB1-UW06V-D Cabinet Loudspeaker with Volume Con-

Cabinet loudspeaker 6 W with volume control, MDF enclosure with fine-woven cloth front, finished in black, with 3 keyholes for wall mounting. Order number LB1-UW06V-D

### LB1-UW06-L Cabinet Loudspeaker

Cabinet loudspeaker 6 W, MDF enclosure with finewoven cloth front, finished in white, with 3 keyholes for wall mounting.

Order number LB1-UW06-L

### LB1-UW06V-L Cabinet Loudspeaker with Volume Control

Cabinet loudspeaker 6 W with volume control, MDF enclosure with fine-woven cloth front, finished in white, with 3 keyholes for wall mounting. Order number LB1-UW06V-L

### Represented by:

### Americas:

Bosch Security Systems, Inc. 12000 Portland Avenue South Burnsville MN 55337, USA Phone: +1-800-392-3497 Fax: +1-800-955-6831 audiosupport@us.bosch.com www.boschsecurity.com

### Europe, Middle East, Africa:

Bosch Security Systems B.V. P.O. Box 80002 5617 BA Eindhoven, The Netherlands Phone: + 31 40 2577 284 Fax: +31 40 2577 330 emea.securitysystems@bosch.com www.boschsecurity.com

### Asia-Pacific:

Robert Bosch (SEA) Pte Ltd, Security Systems 11 Bishan Street 21 Singapore 573943 Phone: +65 6571 2808 Fax: +65 6571 2699 apr.securitysystems@bosch.com www.boschsecurity.asia

### China:

Bosch (Shanghai) Security Systems Ltd. 201 Building, No. 333 Fuquan Road North IBP Changning District, Shanghai 200335 China Phone +86 21 22181111 Fax: +86 21 22182398 www.boschsecurity.com.cn

### America Latina:

Robert Bosch Ltda Security Systems Division Via Anhanguera, Km 98 CFP 13065-900 Campinas, Sao Paulo, Brazil Phone: +55 19 2103 2860 Fax: +55 19 2103 2862 latam.boschsecurity@bosch.com www.boschsecurity.com