

SONKEN DUAL UHF DIGITAL WIRELESS MICROPHONE SYSTEM

Model: WM-600D

Features:

This is superior quality digital wireless UHF Microphone system, which has a transmission range of about 60m. It supports 2 channels and is supplied with two hand held microphones.

The receiver contains two separated unbalanced output for 2 channels and an unbalanced output for 2 channels mixed, and has level controls for each channel; The microphones are powered by 2 x AA batteries (included) and a power adaptor is supplied for the receiver. Ideal for schools, churches, weddings, gyms, karaoke, functions, etc.

Optional belt pack transmitter with lapel or headset microphone, available separately.

Specifications:

Microphone Channels	2ch
Channel Frequency	520.00MHz-694.00MHz
Transmission range	60m
Transmission power	30mW
Battery type	AA
Battery Pack Quantity	2pc included
Packaged Weight	1.55kg
Dimensions: Microphone	240(L) x 50(Dia.) mm, Receiver 210(L) x 140(D) x 42(H) mm
Packaged Length	35.5cm
Packaged Width	30cm
Packaged Height	6.5cm
Warranty	12 Months
AC/DC Power adaptor:	AC100-240V AC @ 50/60Hz to 9V DC @ 0.5Amp

Note:

Handset:

1. The red Led is NOT on in normal use and on when the battery level is low to be replaced.
2. The red Led twinkles once when switching the power on.
3. Always remove the battery after use.
4. Use alkaline battery to avoid leakage.

Receiver:

1. Led of "RF A" or "RF B" is on when the channel A or B works.
2. Led of "PEAK" is on when sound/voice is transmitted.
3. Antennas can be adjusted when effective range varies.